

CAMBRIDGE INTERNATIONAL EXAMINATIONS
Cambridge International Advanced Level

MARK SCHEME for the May/June 2015 series

9608 COMPUTER SCIENCE

9608/33

Paper 3 (Written Paper), maximum raw mark 75

This mark scheme is published as an aid to teachers and candidates, to indicate the requirements of the examination. It shows the basis on which Examiners were instructed to award marks. It does not indicate the details of the discussions that took place at an Examiners' meeting before marking began, which would have considered the acceptability of alternative answers.

Mark schemes should be read in conjunction with the question paper and the Principal Examiner Report for Teachers.

Cambridge will not enter into discussions about these mark schemes.

Cambridge is publishing the mark schemes for the May/June 2015 series for most Cambridge IGCSE[®], Cambridge International A and AS Level components and some Cambridge O Level components.

® IGCSE is the registered trademark of Cambridge International Examinations.

1	(a) (i)	Wrong assignment operator (should be ‘:=’ not ‘=’)	1															
	(ii)	0 is not a digit	1															
	(iii)	‘B’ is not a number	1															
	(b)	<pre> <assignmentstatement> ::= <variable> := <variable><operator><number> <variable> ::= <letter><number> <number> ::= <digit> <digit><number> <letter> ::= A B C <digit> ::= 1 2 3 4 5 <operator> ::= + - * / </pre>	1 + 1 1 1 + 1 1															
	(c) (i)	Use of <u>software</u> ... (idea of using) to implement a <u>hardware</u> set-up (idea of implementing / simulating / emulating)	1 1															
	(ii)	e.g. no need to acquire client hardware for testing / reduces set-up time for test system / common development system for all developers	1															
	(iii)	e.g. software emulation runs slower than real hardware / not possible to emulate some hardware	1															
			Total: 13															
2	(a)	<table border="0" style="width: 100%;"> <thead> <tr> <th style="text-align: center;">Description</th> <th style="text-align: center;">Type of LAN</th> <th></th> </tr> </thead> <tbody> <tr> <td style="border: 1px solid black; padding: 5px;">any packet the listening computer receives may be part of a message for that computer</td> <td style="border: 1px solid black; padding: 5px;">bus with terminators at each end</td> <td style="text-align: center;">1</td> </tr> <tr> <td style="border: 1px solid black; padding: 5px;">connection provided through an access point</td> <td style="border: 1px solid black; padding: 5px;">star</td> <td style="text-align: center;">1</td> </tr> <tr> <td style="border: 1px solid black; padding: 5px;">a process for handling collisions has to be implemented</td> <td style="border: 1px solid black; padding: 5px;">wireless</td> <td style="text-align: center;">1</td> </tr> <tr> <td style="border: 1px solid black; padding: 5px;">listening computer only receives packets that are addressed to this computer</td> <td></td> <td style="text-align: center;">1</td> </tr> </tbody> </table> <p>1 mark for correct arrow(s) from each description</p>	Description	Type of LAN		any packet the listening computer receives may be part of a message for that computer	bus with terminators at each end	1	connection provided through an access point	star	1	a process for handling collisions has to be implemented	wireless	1	listening computer only receives packets that are addressed to this computer		1	
Description	Type of LAN																	
any packet the listening computer receives may be part of a message for that computer	bus with terminators at each end	1																
connection provided through an access point	star	1																
a process for handling collisions has to be implemented	wireless	1																
listening computer only receives packets that are addressed to this computer		1																
	(b) (i)	Server: central computer stores files that are to be downloaded	1 1															

Page 3	Mark Scheme	Syllabus	Paper
	Cambridge International A Level – May/June 2015	9608	33

(ii)	Command: user can send action/instruction (or by example, e.g. change directory) that are carried out on server	1 1
(iii)	Anonymous: allows user to access files user does not need to identify themselves to server	1 1
		Total: 10
3 (a)	A Phishing B Virus C a standalone piece of software which can reproduce itself automatically D sending unsolicited emails to a distribution list	1 1 1 1
(b)	e.g. phishing problem: identity fraud / misuse of financial data solution: ignore email / don't respond to email e.g. virus problem: computer may stop working // lost files solution: running anti-virus software	1 1 or 1 1
(c)	cipher text: encrypted text which is not understandable private key: key only known to owner that can be used to encrypt message to confirm author of message // can be used by owner to decrypt a message thereby ensuring only owner can read message	1 1
(d)	<ul style="list-style-type: none"> • Manager encrypts email • using public key of colleague • colleague decrypts email • using his/her private key 	1 1 1 1
		Total: 12
4 (a) (i)	HomeAddress.ThisHouseNo ← 34	1
(ii)	DECLARE ThisHouseNo: 1..10 DECLARE ThisTown: [Brightown, Arunde, Shoram]	1 1
(b) (i)	TYPE WeatherStation DECLARE StationID : STRING DECLARE Latitude : REAL DECLARE Temperature : <u>ARRAY[1..15]</u> OF INTEGER ENDTYPE	1 1 1 + 1 1
(ii)	StationID is hashed to produce home location If home location is free insert record Else use overflow method to find free location	1 1 1
		Total: 11

5 (a) (i)		<table border="1"> <thead> <tr> <th colspan="3">Circuit 1</th> </tr> <tr> <th>A</th> <th>B</th> <th>X</th> </tr> </thead> <tbody> <tr> <td>0</td> <td>0</td> <td>1</td> </tr> <tr> <td>0</td> <td>1</td> <td>0</td> </tr> <tr> <td>1</td> <td>0</td> <td>0</td> </tr> <tr> <td>1</td> <td>1</td> <td>0</td> </tr> </tbody> </table>	Circuit 1			A	B	X	0	0	1	0	1	0	1	0	0	1	1	0	1
	Circuit 1																				
A	B	X																			
0	0	1																			
0	1	0																			
1	0	0																			
1	1	0																			
(ii)		<table border="1"> <thead> <tr> <th colspan="3">Circuit 2</th> </tr> <tr> <th>A</th> <th>B</th> <th>X</th> </tr> </thead> <tbody> <tr> <td>0</td> <td>0</td> <td>1</td> </tr> <tr> <td>0</td> <td>1</td> <td>0</td> </tr> <tr> <td>1</td> <td>0</td> <td>0</td> </tr> <tr> <td>1</td> <td>1</td> <td>0</td> </tr> </tbody> </table>	Circuit 2			A	B	X	0	0	1	0	1	0	1	0	0	1	1	0	1
Circuit 2																					
A	B	X																			
0	0	1																			
0	1	0																			
1	0	0																			
1	1	0																			
(b) (i)	circuit 1 $\overline{A+B}$ circuit 2 $\overline{A} \cdot \overline{B}$		1 1																		
(ii)	$\overline{A+B} \equiv \overline{A} \cdot \overline{B}$		1																		
(c)	$\overline{(\overline{A \cdot B}) + B}$ mark as : $\overline{(\overline{A \cdot B})}$ $+ B$ bar over whole expression		1 1 1																		
(d)	$\overline{(\overline{A \cdot B}) + B}$ $= \overline{(\overline{A \cdot B})} \cdot \overline{B}$ $= (\overline{A \cdot B}) \cdot \overline{B}$ $= A \cdot (\overline{B \cdot B})$ $= A \cdot 0$ $= 0$ allow f.t. from (c)		1 1 1 1 1 max 3																		
			Total: 11																		

Page 5	Mark Scheme	Syllabus	Paper
	Cambridge International A Level – May/June 2015	9608	33

6 (a)	Control system	1
(b)	Any three different items – max 6 marks heater / water pump / blinds pump ... for altering temperature / watering / light level actuator for... fan for distributing air / water pump / blinds motor analogue to digital converter / digital to analogue convertor ... converts analogue signal from sensor to digital value for processing / converts digital signal to analogue signal for controlling actuator microprocessor ... executes control software warning device (speaker/buzzer/light)... to give warning if conditions out of range / hardware malfunction	1 1 1 1 1 1 1 1 1 1 max 6
(c) (i)	output of system (alter temperature / light level / soil moisture) affects input from sensors continuous	3
(ii)	min / max / ideal / mean / extreme temperature // sampling rate // tolerance interval	1
(iii)	reading from sensor is compared with parameter appropriate action is taken (by example)	2
(d) (i)	reading available for processing reading value is 4	1 1
(ii)	AND #B00000100 // AND #04 // AND #4 1 mark for AND, 1 mark for address mode, 1 mark for mask, 1 mark for indication of numbering system	max 3
		Total: 18