

Cambridge O Level

COMPUTER SCIENCE
Paper 1 Theory
MARK SCHEME
Maximum Mark: 75

Published

This mark scheme is published as an aid to teachers and candidates, to indicate the requirements of the examination. It shows the basis on which Examiners were instructed to award marks. It does not indicate the details of the discussions that took place at an Examiners' meeting before marking began, which would have considered the acceptability of alternative answers.

Mark schemes should be read in conjunction with the question paper and the Principal Examiner Report for Teachers.

Cambridge International will not enter into discussions about these mark schemes.

Cambridge International is publishing the mark schemes for the May/June 2022 series for most Cambridge IGCSE, Cambridge International A and AS Level and Cambridge Pre-U components, and some Cambridge O Level components.

Cambridge O Level – Mark Scheme

PUBLISHED

Generic Marking Principles

These general marking principles must be applied by all examiners when marking candidate answers. They should be applied alongside the specific content of the mark scheme or generic level descriptors for a question. Each question paper and mark scheme will also comply with these marking principles.

GENERIC MARKING PRINCIPLE 1:

Marks must be awarded in line with:

- the specific content of the mark scheme or the generic level descriptors for the question
- the specific skills defined in the mark scheme or in the generic level descriptors for the question
- the standard of response required by a candidate as exemplified by the standardisation scripts.

GENERIC MARKING PRINCIPLE 2:

Marks awarded are always whole marks (not half marks, or other fractions).

GENERIC MARKING PRINCIPLE 3:

Marks must be awarded **positively**:

- marks are awarded for correct/valid answers, as defined in the mark scheme. However, credit is given for valid answers which go beyond the scope of the syllabus and mark scheme, referring to your Team Leader as appropriate
- marks are awarded when candidates clearly demonstrate what they know and can do
- marks are not deducted for errors
- marks are not deducted for omissions
- answers should only be judged on the quality of spelling, punctuation and grammar when these features are specifically assessed by the question as indicated by the mark scheme. The meaning, however, should be unambiguous.

GENERIC MARKING PRINCIPLE 4:

Rules must be applied consistently, e.g. in situations where candidates have not followed instructions or in the application of generic level descriptors.

© UCLES 2022 Page 2 of 13

GENERIC MARKING PRINCIPLE 5:

Marks should be awarded using the full range of marks defined in the mark scheme for the question (however; the use of the full mark range may be limited according to the quality of the candidate responses seen).

GENERIC MARKING PRINCIPLE 6:

Marks awarded are based solely on the requirements as defined in the mark scheme. Marks should not be awarded with grade thresholds or grade descriptors in mind.

Please note the following further points:

The words in **bold** in the mark scheme are important text that needs to be present, or some notion of it needs to be present. It does not have to be the exact word, but something close to the meaning.

If a word is underlined, this exact word must be present.

A single forward slash means this is an alternative word. A double forward slash means that this is an alternative mark point.

Ellipsis (...) on the end of one-mark point and the start of the next means that the candidate **cannot** get the second mark point without being awarded the first one. If a mark point has an ellipsis at the beginning, but there is no ellipsis on the mark point before it, then this is just a follow-on sentence and **can** be awarded **without** the previous mark point.

© UCLES 2022 Page 3 of 13

Question		Answer	Marks			
1(a)	One mark for each correct line					
	Denary	8-bit binary				
		00100001				
	41	10100110				
		00101001				
	174					
		10000110				
	86	10101110				
		01010110				
1(b)	One mark for correct working, one mark for	correct answer	2			
	Working e.g. • 256 + 64 + 16 + 4 + 2 + 1					
	Answer: • 343					

								LISHED			
uestion								Answer			Marks
2(a)	Two	Two marks each correct conversion (one mark for the first four bits, one mark for the second four bits)									
	2F	0	0	1	0	1	1	1	1		
	15	0	0	0	1	0	1	0	1		
	D6	1	1	0	1	0	1	1	0		
2(b)	• II • E • A	Assemb JRL // \ /Iemory		ige // low- ess	-level lanç	guage					2
2(c)	Struct Let Fresco	cture Layout e.g. Wh entation	or a descr of the we ere text is on ting of the colour of	eb page s placed e web pa		or a corre	ct exampl	e			

© UCLES 2022 Page 5 of 13

Question	Answer	Marks
2(d)	Two from:	2
	 The formatting of the page can be changed/edited without needing to alter the structure so, they can make regular updates without needing to check the structure 	
	 The formatting document can be used again for a different website If further content and web pages are added to the website, the necessary formatting can be easily applied so, this can save time when developing/updating a website Allows use of CSS to standardise formatting so, CSS only needs to be created once (to be applied to each webpage) 	

© UCLES 2022 Page 6 of 13

Question	Answer					
3(a)	One mark for the co	orrect term or definition		5		
		Term	Definition			
		browser	Software/application that allows users to view web pages / render HTML			
		Internet Service provider // ISP	this is the company that provides a user with a connection to the Internet			
		HTTP // HTTPS	this is a protocol that is used to send data for web pages across the Internet			
		Uniform Resource Locator (URL)	a text-based version of a web address			
		cookie	a text file (stored by web browser) that contains data about a user's browsing habits/details/preferences			
3(b)	Hardware or so	oftware based		1		
3(c)	Four from:			4		
	 such as a wlThe firewall will	hitelist/blacklist of website	ncoming and outgoing from her computer			

© UCLES 2022 Page 7 of 13

Question	Answer	Marks
4(a)	Any three from: It uses English-like statements It needs to be converted to machine code (to be processed by a computer) using a translator It is portable One line of code can perform multiple commands	3
4(b)(i)	 Two from: The user is not allowed to access the source code so, they cannot tailor the software to their needs so, they cannot fix any bugs in it The software is still covered by copyright The user must get the owner's permission to do anything beyond using it 	2
4(b)(ii)	 Two from: The user can access the source code so, they can tailor the software to their needs so, they can fix any bugs in it so, the source code could be studied for educational purposes The user can redistribute the software/program but this must be done under the same terms as the original software 	2

© UCLES 2022 Page 8 of 13

Question				Answer		Marks
5(a)	One mark for each correct logic gate with correct input(s)					5
	А————————————————————————————————————					
5(b)	Four marks Three mark Two marks One mark fo	s for 6/7 core for 4/5 corre	rect outputs ect outputs			4
	Α	В	С	Working space	Х	
	0	0	0		0	
	0	0	1		0	
	0	1	0		0	
	0	1	1		1	
	1	0	0		0	
	1	0	1		0	
	1	1	0		0	
	1	1	1		1	

© UCLES 2022 Page 9 of 13

Question	Answer	Marks
6(a)	One mark for identifying the attack, two marks for the description	6
	 Phishing Email is sent to user to encourage them to click link that takes user to fake website 	
	Pharming • Email is sent to user to encourage them to click link/download attachment • that triggers download of malicious code that will redirect user to fake website	
	Virus/malware • Email is sent to user to encourage them to click link/download attachment • that triggers download of virus/malware	
	Denial of service // DoS A very large number of emails are sent to a server/network at the same time crashing the server/network	
6(b)	Any two from:	2
	 Encryption Password Two-step / Two-factor authentication/verification Biometric device Anti-malware // Anti-virus Proxy-server 	

© UCLES 2022 Page 10 of 13

Question	Answer	Marks
6(c)	One mark for identifying an issue, one mark for suggesting a suitable prevention	6
	Power surge/loss (damages hardware)	
	 Use a UPS 	
	Water can be spilled on the device	
	 Don't have water near the device 	
	Keep device in a waterproof box when not is use	
	Fire can destroy device	
	 Use electrics safety 	
	Keep device in a fireproof box when not is use	
	Data is accidentally deleted	
	 Add verification method for data deletion 	
	 Set access levels for data to limit who can delete the data 	
	 Incorrect use of storage device 	
	Making sure device is ejected before removing	
	Physical damage to hardware // hardware failure	
	Correct care and maintenance of hardware	
	 Software failure 	
	 Making sure it is always up to date // enable automatic updates 	

© UCLES 2022 Page 11 of 13

Question	Answer				Marks
7(a)	Three from: CD DVD Blu-ray				3
7(b)	One mark for each correct row				6
		Ту	pe of storaç	ge	
	Statement	Magnetic (✓)	Optical (✓)	Solid state (✓)	
	this storage has no moving parts			✓	
	this storage uses a laser to read and write data		✓		
	this storage uses a read/write head	✓	✓		
	this storage burns pits onto a reflective surface		✓		
	this storage uses NAND and NOR technology			✓	
	this storage stores data in tracks and sectors	✓	(✓)		

© UCLES 2022 Page 12 of 13

Question	Answer	Marks
8(a)	 Any four from: Trial version of software for a limited time / number of uses with limited features free of charge If full version is required need to pay fee / sign up // When trial over user is asked to pay / sign up Protected by copyright Type of software licence 	4
8(b)	e.g. Copyright Plagiarism Production/distribution of malware Intellectual property theft Privacy of data Age appropriation Offensive materials Environmental impact of distribution media e.g. CDs Accessibility of software Security of software Following guidelines of professional bodies e.g. ACM/IEEE/BCS	3

© UCLES 2022 Page 13 of 13